



DD0SR-1Z

Decora Smart Switch Companion for Multi-Location Switching, 120VAC, 60Hz

The Decora Smart Switch Companion is designed for use in a multi-location application only and must be used with a Leviton Decora Smart or Decora Digital switch, dimmer or fan speed control allowing the lighting or fan to be controlled from more than one location. Its stylish look is compatible with Leviton's other Decora devices and wallplates (sold separately). White face assembled on device with ivory and light almond face plates included. Change the color of the switch at any time by ordering a new face plate color change kit (DDKIT-S). Face plate colors include white, ivory, light almond, gray, black and brown

Color :  White, Ivory, Light Almond

UPC Code : 078477728574

Country Of Origin : China

- PRACTICAL – Turn lights or fan on/off from multiple locations
- VERSATILE – Can use in 3-way or up to 9 additional locations when used with primary Decora Smart (Z-Wave, Wi-Fi, Zigbee, HomeKit) OR Decora Digital switches, dimmers, or fan speed controls
- FLEXIBLE – Alternative wiring method available for applications where a neutral wire is not present (see product instruction sheet)
- STYLISH – Modern appearance that coordinates with other Leviton Decora devices
- CONVENIENCE - Change the switch faceplate color to black, gray, brown, light almond, ivory or white using DDKIT-S

[Have Questions? Search the knowledge base.](#)

Technical Information

Product Features

Action : Rocker Switch for ON /OFF

Available Colors : White-W, Ivory-I, Light Almond-T, Gray-G, Black-E, Brown-B

Color : White, Ivory, Light Almond

Color Change Kit : DDKIT-S

Feature : 3-way or Up to 9 Location Applications

Grounding : Grounding

Light : None

Pole : 3

Standards and Certifications
: CSA, NOM

Style Name : Decora

Termination : Side

Torque Range : 14 – 18 in.-lbs

Type : Companion Device

Voltage : 120 VAC

Wallplate : Order Separately

Warranty : 5-Year Limited

Wiring Notes : Neutral or load side required. For use with 120VAC applications only

Features and Benefits

- The Decora Switch Companion **must** be used with a primary Decora Smart (Wi-Fi, Z-Wave, HomeKit or Zigbee) or Decora Digital switch, dimmer or fan speed control
- For 120VAC applications
- For use in 3-way or up to 9 additional locations
- Neutral wire or load side required for installation
- White face assembled on device, Ivory and Light Almond faces included
- Change the switch faceplate color to black, gray, brown, light almond, ivory or white using DDKIT-S

Patents ^{*}

US8944859

This list is provided for patent marking purposes only. A good faith effort is made to maintain the accuracy and completeness of this list. No legal inference should be drawn from the omission of a patent from this list.

Leviton Manufacturing Co., Inc

201 North Service Road, Melville, NY 11747

Telephone: +1-800-323-8920 · FAX: +1-800-832-9538 · Tech Line (8:30AM-7:30PM E.S.

T. Monday-Friday): +1-800-824-3005

Leviton Manufacturing of Canada, Ltd.

165 Hymus Boulevard, Pointe Claire, Quebec H9R 1E9 · Telephone: +1-800-461-2002 · FAX: +1-800-824-3005 ·

Leviton S. de R.L. de C.V.

Lago Tana 43, Mexico DF, Mexico CP 11290 · Tel.: (+52)55-5082-1040 · FAX: (+52) 5386- 1797 ·

Visit our Website at: www.leviton.com

© 2025 Leviton Manufacturing Co., Inc. All Rights Reserved. Subject to change without notice.

Leviton has a global presence.

If you would like to know where your local Leviton office is located please go to:

www.leviton.com/company/about-leviton/locations

© 2025 Leviton Manufacturing Co., Inc.